

# **Technical Specification**

Of

## **Direct Current Distribution Board**

Specification no – BSES-TS-71-DCDB-R0

Rev:		0
Pages:		1 of 16
Date:	1	02 May 2022
0	Abhishek Harsh	tom .
Prepared by	Amar Singh	Ameelengh
Reviewed by	Srinivas Gopu	tori.
	Abhinav Srivastava	Aptiment
	Gaurav Sharma	Ceanean 14
Approved by	Gopal Nariya	0×



## **INDEX**

1	SCOPE	3
2	STANDARDS AND CODES	3
3	SERVICE CONDITION	3
4	CONSTRUCTION	4
5	CONFIGURATION	5
6	BUSBARS	6
7	TERMINALS AND WIRING	6
8	METERS, INDICATIONS, PUSH BUTTONS & HEATERS	7
9	NAME PLATES & MARKINGS	7
10	FINISH	8
11	APPROVED MAKES OF COMPONENTS	8
12	INSPECTION AND TESTING	9
13	PACKING, SHIPPING, HANDLING AND SITE SUPPORT	9
14	DEVIATIONS	10
15	DOCUMENT SUBMISSION	0
16	GUARANTEED TECHNICAL PARTICULARS	11



## 1 SCOPE

This specification covers the design, engineering, manufacture, assembly and testing at Manufacturer's works and supply of 220 VDC/50 VDC Distribution board (DCDB) along with all hardware and accessories required for installation and operation.

Specification covers Type 1 and Type 2 DCDB. Type 1 DCDB is for Grid Substations while Type 2 DCDB is for BSES HT Customers.

#### 2 STANDARDS AND CODES

2.1	IS:8623	Specification for factory built assemblies of switchgear & control gear for voltages up to and including 1000V AC/1200 V DC.
2.2	IS 60947-1	Specification for Low-voltage Switchgear and Controlgear - Part 2 :Circuit Breakers
2.3	IS:10118	Code of practice for selection, installation and maintenance switchgear and control gear
2.4	IS:2705	Current transformers
2.5	IS:3231	Electrical relays for power system protection
2.6	IS:1248	Electrical Indicating instruments
2.7	IS:4794	Switches and push buttons
2.8	IS:6005	Code of practice of phosphating iron and steel
2.9	IS:5082	Wrought Aluminium and aluminum alloys for electrical purposes
2.10	IS 3043	Code of practice for Earthing

## 3 SERVICE CONDITION

3.1	Location	Indoor
3.2	Average grade atmosphere	Heavily polluted, Dry
3.3	Maximum altitude above sea level	1000M
3.4	Ambient air temperature	Highest 50Deg C Average 40Deg C
3.5	Minimum ambient air temperature	0 Deg C
3.6	Relative Humidity	100%



3.7	Rainfall	750mm concentrated in four months
3.8	Seismic Zone	IV

#### **4** CONSTRUCTION

4.1	General construction	It shall be free-standing type comprising dust-tight and vermin-proof sheet steel cabinets suitable for indoor installation with IP-54 degree of protection. Necessary busbar support insulators, cable glands, cable supports and terminal blocks etc. The board shall preferably be of single front type.
4.2	Material	The Board shall be made cold rolled steel sheet having Thickness of 2.5 mm of load bearing member and 2 mm for Doors and covers, suitably reinforced to provide flat level surfaces. No welds, rivets, hinges or bolts shall be visible from outside.
4.3	Equipment Mounting	All switches provided on the distribution board shall be on front side of the cabinets, operable from outside. All instruments and control devices shall be mounted on the front of cabinets and fully wired to the terminal blocks.
4.4	Busbar housing	The busbars shall be housed in totally enclosed busbar chambers. Incoming connections from the busbar to various feeders shall be designed so as not to disturb cable connections. Busbar arrangement should ensure safety of the operation/maintenance personnel and facilitate working on any outgoing module without the need for switching off in-feed to the adjacent modules, as far as possible
4.5	Cable alleys	A cable alley preferably 230 mm wide shall be provided in each vertical section for taking cables into the compartments. Cable alleys shall be provided on sides of busbar chamber.
4.6	Cable entry	Cable entry should be from bottom
4.7	Cable glands	Compression type cable glands shall be provided to hold the cables to avoid any pressure or tension on the terminal block connections.
4.8	Gland Plate	Gland plate shall be 3.0mm thick.
4.9	Doors	The doors of cabinets shall be lockable and shall be fitted with double lipped gaskets.
4.10	Gasket	All doors, removable covers and panels shall be gasketed all around with neoprene gaskets. Gaskets shall be embedded through machine only.
4.11	Ventilating louvers	Ventilating louvers shall have screens and filters. The screens shall be made of either brass or GI wires mesh.



4.12	Foundation	The panels shall be fixed on the embedded foundation channels with intervening layers anti vibration strips made of shock absorbing materials.
4.13	Base Frame	Base frames shall be supplied along with panels. 100mm channel painted black.
4.14	Mounting	Equipment on front of panel shall be flush mounted. No equipment shall be mounted on the doors.
4.15	Working level	The center lines of switches, push buttons and indicating lamps shall not be less than 750mm and higher than 1600mm from panel base.
4.16	Dimension	500(L)X500(D)X1800(H) mm <sup>3</sup>

#### 5 CONFIGURATION

5.1	Incomers	One incomers	s having Dou	ble Pole DC	C MCB with A	ux Switch.
5.2 Outgoing feeders		All outgoing feeders shall have MCB. Number of outgoing feeders shall be as per table attached				
			Type-1		Type-2	
Application		No of Poles	Rating of MCB (In Amp)	Quantity	Rating of MCB (In Amp)	Quantity
Income	r	2	100	1	50	1
Emergency Lighting DB		2	32	1	16	1
Fire Alarm System		2	32	1	16	0
SCADA		2	32	2	16	1
CRP/33 kV/66 kV Switchgear		2	32	4	16	1
11 kV Switchgear		2	32	4	16	0
Testing Purpose		2	32	1	16	1
NIFPS		2	32	4	16	0
Spare 1		2	100	1	50	1
Spare 2		2	32	4	16	2



#### 6 BUSBARS

6.1	Material	Busbar shall be of tinned electrolytic copper or Aluminium
6.2	Size	Suitable for carrying the rated continuous current of 100 A and short circuit current of 15 kA. Busbars shall be continuous throughout the panel. Temperature rise should be limited to 40 degrees over ambient.
6.3	Supports	The busbar shall be supported by means of durable non-hygroscopic, non-combustible and non-tracking polyester fiberglass material or porcelain. Supports shall be capable of withstanding the maximum short circuit stresses.
6.4	Sleeves and shrouds	Busbars shall be encased in heat-shrinkable sleeves of insulating material which shall be suitable for the operating temperature of busbars during normal service. The busbar joints shall be provided with removable thermosetting plastic shrouds.

#### 7 TERMINALS AND WIRING

7.1	Wiring	
7.1.1	Grade and type	1100 V grade, PVC insulated, FRLS type stranded flexible copper wire.
7.1.2	Ferruling	Each wire shall bear an identifying ferrule or tag at each end or connecting point.
7.1.3	Spare	20% Spare Wiring
7.2	Terminals	Terminals of appropriate size shall be provided inside each cabinet for incoming and outgoing cables.
7.2.1	Grade	1100 V grade, moulded piece terminals complete with insulated barriers, washers, nuts and lock nuts.
7.2.2	Power Terminals type	Stud type, nut driver operated
7.2.3	Control terminals type	Stud type, screw driver operated
7.2.4	Spare terminals	20% spare terminals should be provided in each terminal block.
7.2.5	Accessibility	Placement of terminals shall enable proper cable termination. Terminals shall be readily accessible for inspection and maintenance.
7.2.6	Marking	The terminals shall be serially numbered to facilitate installation and maintenance.



### 8 METERS, INDICATIONS, PUSH BUTTONS & HEATERS

8.1	Meters	
8.1.1	Ammeter	DC Moving coil ammeter of size 96 sq.mm. with external shunt. Rating of Ammeter shall be 0-100A DC.
8.1.2	Voltmeter	DC Moving coil voltmeter of size 96.sq.mm to read the DC Bus voltage. Rating of Voltmeter shall be 0-300VDC
8.1.3	Туре	Digital type, connected through instruments transformers of suitable rating.
8.2	Indicating lamps	Indicating lamps shall be of low wattage cluster LED type.
8.2.1	Incomer/ Outgoing On	Red
8.2.2	Incomer/ Outgoing Off	Green
8.2.3	Incomer/ Outgoing Trip	Amber
8.3	Push buttons	For manual operation of incomer MCB
8.4	Heaters	Cubicle space heater having rating of 100W. Thermostat for space heater shall be provided with temperature range 0-90 <sup>0</sup>
8.5	CFL	Cubicle lamp shall be provided in DCDB having rating of 11 W.

#### 9 NAME PLATES & MARKINGS

9.1	Panel nameplate	Panel shall have a nameplate clearly indicating the following: a. Panel Serial No b. Customer Name - BSES Yamuna/Rajdhani Power Ltd c. PO No. & date - d. Type of Panel - e. Current rating - f. Guarantee period -
9.2	Feeder nameplate	Large and bold name plate carrying the feeder identification shall be provided on the top.
9.3	Equipment nameplate	<ul> <li>a. All equipment mounted on front side as well as equipment mounted inside the panels shall be provided with individual name plates with equipment designation engraved.</li> <li>b. All front mounted equipment shall be also provided</li> </ul>



		at the rear with individual name plates engraved with tag numbers corresponding to the one shown in the panel internal wiring to facilitate easy tracing of the wiring.
9.4	Material	Non-rusting metal or 3 ply lamicoid. Nameplates shall be black with white engraving lettering. Stickers are not allowed.
9.5	Fixing	All nameplates/rating plates shall be riveted to the panels at all four corners. Bolting/screwing is not acceptable.
9.6	Markings	Each switch shall bear clear inscription identifying its function. Similar inscription shall also be provided on each device whose function is not other wise identified. If any switch or device does not bear this inscription separate nameplate giving its function shall be provided for it. Switch shall also have clear inscription for each position indicating e.g. Trip-Neutral close, ON-OFF etc.

#### 10 FINISH

10.1	Primer	Two coats
10.2	Paint	Two finishing coats of epoxy based paint of Shade RAL 7032 with glossy finish.
10.3	Paint thickness	50 microns (minimum)

#### 11 APPROVED MAKES OF COMPONENTS

11.1	Switch	Siemens / L&T (Salzer)
11.2	HRC Fuse Links	GE/ Siemens/ L&T
11.3	Meters	Rishabh/Schneider/AE
11.4	Terminals	Connectwell/Elmex/Wago/Phoenix
11.5	Push buttons / Actuator	L&T/Siemens/Vaishno/Schneider
11.6	МСВ	Datar/Legrand/Hager/Schneider/ABB
11.7	Indicating lamps	Vaishno/Binay/Teknic/Siemens/Mimic/C&S



### 12 INSPECTION AND TESTING

12.1	Type test	Equipment should be of type tested quality only, type test certificate to be submitted along with offer. If the manufacturer's lab is accredited by govt. / authorized body then it shall be acceptable for type testing.
12.2	Acceptance & Routine tests	As per relevant Indian standard

### 13 PACKING, SHIPPING, HANDLING AND SITE SUPPORT

13.1	Packing Protection	The packing shall be fit to withstand rough handling during transit and storage at destination. The test set should be properly protected against corrosion, dampness & damage.		
13.2	Packing for accessories and spares	Robust non-returnable packing case with all the above protection & identification Label. The bidder should get the packing list approved before dispatching the material.		
13.3	Packing Identification Label	On each packing case, following details are required:		
13.3.1	Individual serial number			
13.3.2	Purchaser's name			
13.3.3	PO number (along with SAP item code, if any) & date			
13.3.4	Equipment Tag no. (if any)			
13.3.5	Destination			
13.3.6	Manufacturer / Supplier's name			
13.3.7	Address of Manufacturer / Supplier / it's agent			
13.3.8	Description			
13.3.9	Country of origin			
13.3.10	Month & year of Manufacturing			
13.3.11	Case measurements			



13.3.12	Gross and net weight			
13.3.13	All necessary slinging and stacking instructions			
13.4	Shipping The seller shall be responsible for all transit damage due to improper packing.			
13.5	Handling and Storage	Manufacturer instruction shall be followed.		
13.6	Detail handling & storage in commencement of supply.	struction sheet / manual to be furnished before		

#### 14 DEVIATIONS

14.1 Deviation Deviation with the tender by refere clause/GTP/Drawing and a desc alternative offer. In absence of s be assumed that the bidder con specification. No deviation will b order.
--

#### 15 DOCUMENT SUBMISSION

Drawing submission shall be as per the matrix given below. All documents/ drawing shall be provided on A3/A4 sheet in box file with separators for each section. Also provide USB containing pdf with bid for soft copy. Language of the documents shall be English only. Deficient/ improper document/ drawing submission may liable for rejection

S. No	Head	Bid	Drawing Approval	Pre Dispatch	Pre Closure
15.1	Contact Person Name, Email ID and Mobile Number	Required			
15.2	Deviation Sheet	Required	Required		
15.3	Type Test	Required			
15.4	Any Technological Advancement in DCDB	Required			
15.5	Manufacturer's quality assurance plan and certification for quality standards				
15.6	General Arrangement		Required		
15.7	Door Layout		Required		



15.8	Internal Layout		Required		
15.9	SLD		Required		
15.10	Schematic Circuit diagram		Required		
15.11	Bus Bar Arrangement		Required		
15.12	Cable Alley Arrangement		Required		
15.13	GTP	Required	Required		
15.14	QAP		Required		
15.15	BOQ		Required		
15.16	Foundation diagram		Required		
15.17	TB Detail		Required		
15.18	Name Plate Detail		Required		
15.19	Make of all Component as per specification		Required		
15.20	Inspection Report			Required	
15.21	As manufacturing Drawings			Required	
15.22	Operation and Maintenance Manual			Required	Required
15.23	Trouble shooting manual			Required	Required
15.24	As built Drawings				Required
15.25	Test Report				Required

#### **16 GUARANTEED TECHNICAL PARTICULARS**

Vendor must submit clause wise compliance in Excel sheet against specification at the time of drawing approval clearly highlighting the deviations from specification against each clause.

S. No.	Description	Specification requirement	Bidder's Data
16.1	GENERAL FEATURES		
16.1.1	Make		
16.1.2	Туре		
16.1.3	Reference Standard		



16.1.4	Rated Operational voltage	220 VDC/50 VDC	
16.1.5	Rated Nominal Current	100	
16.1.6	Rated Insulation voltage	1100V	
16.1.7	Rated Impulse withstand voltage	8kV	
16.1.8	Service supply for heating, lighting and power sockets	240VAC±10%	
16.1.9	Mounting	Floor (Free standing)	
16.1.10	Connections	Cable entry – Bottom	
16.1.11	Configuration	Single front	
16.1.12	Enclosure thickness		
а	Load Bearing Member	>=2.5mm	
b	Doors and Covers	>=2 mm	
С	Gland Plate	3 mm	
16.1.13	Enclosure Material	CRCA Sheet	
16.1.14	Enclosure degree of protection	IP 54	
16.1.15	Power Cable Termination	Suitable for 4CX50 Sq.mm Al	
16.1.16	Paint shade	RAL 7032 (Siemens Grey)	
16.1.17	Typical vertical section (Overall dimension (mm) and weight ( Kg))		
16.1.18	Incomer	Required	
16.1.19	Outgoings		
16.1.20	Dimensions of the DCDB Panel	500(L)X500(D)X1800(H) mm3	
16.1.21	Weights of the DCDB Panel	(in kg.)	
16.1.22	Marking on the panel	As per the specification	
16.1.23	Cable Alley Width	230 mm	
16.1.24	Cable Gland	Compression Type	



16.1.25	Gasket Material	Neoprene	
16.1.26	Ventilating louvers	Required	
16.1.27	Base Frame	100mm channel	
16.2	МСВ		
16.2.1	Make	Datar/Legrand/Hager/Schneider/ABB	
16.2.2	Incomer	100A/50 A	
16.2.3	Emergency Lighting DB	32A/16 A	
16.2.4	Fire Alarm System	32A/16 A	
16.2.5	SCADA	32A/16 A	
16.2.6	CRP	32A/16 A	
16.2.7	11 kV Switchgear	32A/16 A	
16.2.8	Testing Purpose	32A/16 A	
16.2.9	NIFPS	32A/16 A	
16.2.10	Spare 1	100A/50 A	
16.2.11	Spare 2	32A/16 A	
16.3	BUS AND BUS TAPS		
16.3.1	Make		
16.3.2	Material	Tinned electrolytic copper or Aluminum	
16.3.3	Reference standard		
16.3.4	Continuous Current (at site condition, 50°C ambient) within cubicle		
16.3.5	Short Circuit withstand Current for 1 sec	15 KA	
16.3.6	Cross sectional Area		
16.3.7	DC resistance	ohm/m/ph	



16.3.8	Reactance	ohm/m/ph	
16.3.9	Losses-middle phase	w/m/ph	
16.3.10	Minimum clearance of bus bar and joints	Required	
16.3.11	Phase to phase (mm)		
16.3.12	Phase to earth (mm)		
16.3.13	Bus bar insulation	<ul> <li>Heat shrinkable sleeves rated for maximum operating voltage</li> <li>Cast resin shrouds for joint</li> </ul>	
16.3.14	Bus joints	Silver	
16.3.15	Bus bar support insulator	Required	
16.3.16	Spacing (mm)		
16.3.17	Make		
16.3.18	Туре		
16.3.19	Reference standard		
16.3.20	Voltage class (kV)		
16.3.21	Minimum creepage distance (mm)		
16.3.22	Cantilever strength (Kg/sq.cm.)		
16.4	Wiring and Terminals		
16.4.1	Wiring		
а	Grade and type	1100 V grade, PVC insulated, FRLS type stranded flexible copper wire.	
b	Ferruling	Each wire shall bear an identifying ferrule or tag at each end or connecting point.	
С	Spare	20% Spare Wiring	
16.4.2	Terminals		
а	Grade	1100 V grade, moulded piece terminals complete with insulated barriers, washers, nuts and lock nuts.	
b	Power Terminals type	Stud type, nut driver operated	
С	Control terminals type	Stud type, screw driver operated	



d	Spare terminals	20% spare	
е	Accessibility	Placement of terminals shall enable proper cable termination. Terminals shall be readily accessible for inspection and maintenance	
f	Marking	The terminals shall be serially numbered to facilitate installation and maintenance.	
16.5	METERS, INDICATIONS, PUSH BUTTONS & HEATERS		
16.5.1	Ammeter	DC Moving coil ammeter of size 96 sq.mm. with external shunt. Rating of Ammeter shall be 0-100A DC.	
а	Model No Ammeter		
b	Make of Ammeter		
16.5.2	Voltmeter	DC Moving coil voltmeter of size 96.sq.mm to read the DC Bus voltage. Rating of Voltmeter shall be 0-300VDC	
а	Model No Voltmeter		
b	Make of Voltmeter	Rishabh/Schneider/AE	
С	Туре	Digital type	
16.5.3	Indicating lamps	Cluster LED type.	
а	Make of Indicating lamps	Vaishno/Binay/Teknic/Siemens/Mimic/C &S	
b	Incomer/ Outgoing On	Red	
с	Incomer/ Outgoing Off	Green	
d	Incomer/ Outgoing Trip	Amber	
е	Push buttons Make	L&T/Siemens/Vaishno/Schneider	
16.5.4	Heaters	Cubicle space heater having rating of 100W. Thermostat for space heater shall be provided with temperature range 0-90 <sup>0</sup>	
16.5.5	CFL	Cubicle lamp shall be provided in DCDB having rating of 11 W.	



16.6	NAME PLATES & MARKINGS		
а		Panel Serial No	
b		Customer Name - BSES Yamuna/Rajdhani Power Ltd	
с	Panel nameplate	PO No. & date -	
d		Type of Panel -	
е		Current rating -	
f		Guarantee period -	
16.6.1	Feeder nameplate	As per Spec	
а	Equipment nameplate	As per Spec	
b	Material	As per Spec	
с	Fixing	As per Spec	
d	Markings	As per Spec	
16.7	FINISH		
а	Primer	Two coats	
b	Paint	Two finishing coats of epoxy based paint of Shade RAL 7032 with glossy finish.	
с	Paint thickness	50 microns (minimum)	